Technical Bulletin
No: 106 – Timer Auto Only Operation

Model: RS-6/12/18/24 **No:** 106

Subject: Timer Auto Only Operation **Date:** 03/03/95

Purpose: Occasionally a customer prefers to use the location of the timer switch board for another application.

Solution: Modify the timer board to always operate in the "Auto" mode.

Procedure:
1. Disconnect J3 from the timer board.
2. Remove the timer switch board assembly from the console.
3. Connect the anode of a 1N4148 diode to J3 Pin 6. Connect the cathode to J3, Pin 7
4. Connect the anode of a second 1N4148 diode to J3, Pin4. Connect the cathode to J3, Pin 7

601 Heron Drive
Logan Township, NJ 08085
Phone: 856-467-8000 • Fax: 856-467-3044
http://www.radiosystems.com